

1. ELECTRICAL SPECIFICATIONS

- AC voltage range detection: 100 ÷ 1000V AC to ground
- Frequency range: 50/60Hz
- Phase sequence indication with 1-wire
- Conformity test with 1-wire
- Safety: IEC/EN61010-1
- Category of measurement: CAT IV 1000V
- Insulation: double insulation
- Pollution degree: 2

2. GENERAL SPECIFICATIONS

- Red LED indication => incorrect phase sequence indication
- Green LED indication => correct phase sequence indication
- Buzzer indication
- Power supply: 2x1.5V batteries alkaline type AAA NEDA24A LR03
- Working temperature: -10°C ÷ 50°C
- Working humidity: <75%HR (-10°C ÷ 40°C)
<45%HR (40°C ÷ 50°C)
- Dimensions (L x W x H) : 160x26x20mm
- Weight (included batteries): 48g



Incorrect phase sequence



Correct phase sequence

This product conforms to the prescriptions of the European directive on low voltage 2006/95/EEC and to EMC directive 2004/108/EEC





HT70

Rel. 1.01 - 20/01/2014

Pen phase sequence indicator anc conformity test

Pag 2 of 2



HT ITALIA SRL
Via della Boaria, 40
48018 - Faenza (RA) - Italy
T +39 0546 621002 | F +39 0546 621144
M export@ht-instruments.com | ht-instruments.com

WHERE
WE ARE

